

# IIT(BHU) SSID WI-FI CONNECTIVITY


**Step 1:** Click on **SSID: IIT(BHU)**



**Step 2:** Provide Username & Password in Network authentication Pop-up.




**Step 3:** Click on **Connect** in Pop-up during Windows security alert.




**Step 4:** if you are not able to connect **IIT(BHU)** SSID using this way, then your PC wireless adapter may be using the Certificate for authentication which will not provide the credentials Pop-up. In that case use step 5 to 16.


**Step 5:** Open the control panel and click manage wireless network tab.



**Step 6:** Click on Add tab as shown in below image.



**Step 7:** Click on manually create a network profile.




**Step 8:** Fill the details as shown in below image:


Network Name: **IIT(BHU)**

Security Type: **WPA2-Enterprise**


Encryption-type: **AES**




**Step 9:** Click on change connection settings:




**Step 10:** it will show as below image. Now click on security tab.




**Step 11:** Fill the details as below:




**Step 12:** Click on settings tab, un-tick the validate server certificate & Select authentication method: Secured password (EAP-MSCHAP v2).








**Step 13:** Click on Configure tab, un-tick the automatic option for windows connecting.




**Step 14:** Now Click on Advanced settings, and click the specify authentication mode:




**Step 15:** Tick on authentication method, drop down the option list and select user authentication option.



**Step 16:** Save the authentication advanced setting and un-tick remember my credentials option.



**Step 17:** Now user are connected with IIT internal network, to access the internet. The browser will generate the Captive portal for user authentication. Provide the same username & password again to access the internet.

A screenshot of a web browser window displaying a captive portal for authentication. The page has a grey background and features the IIT Institute of Technology logo at the top. The main heading is 'Authentication Required'. Below the heading, it says 'Please enter your username and password to continue.' There are two input fields: 'Username:' and 'Password:'. A 'Continue.' button is located at the bottom right of the form area.

**Step18:**After Successful login user can access internet.

A screenshot of the search input field on the Google India homepage. It is a simple, empty rectangular box with a thin blue border.

Google Search

I'm Feeling Lucky

Google.co.in offered in: हिन्दी বাংলা తెలుగు मराठी தமிழ் ગુજરાતી ಕನ್ನಡ മലയാളം ਪੰਜਾਬੀ

